# **SPECIFICATIONS**

**OF** 

# **VIBRATION DETECTION SWITCH**

**MODEL NAME: D7E-1** 

OUTLINE DRAWING NO. 6 4 2 1 3 7 7 - 0

WRITTEN: Y. Kamihashi Aug 6, 1997 CHECKED: S. Mori Aug. 6, 1997

APPROVED: N. Ashikaga Aug. 6, 1997

# **OMRON CORPORATION**

**OMRON** 

1. CONSTRUCTION DRWG. No. 6 4 2 1 3 7 7 - 0 1-1 Outline dimensions To output the ON/OFF signal by mechanical switching 1-2 Switching mechanism of the internal switch contact by vibration. IP67 (Only internal switch) 1-3 Enclosure rating 130 to 200 gal\* (cycle: 0.3, 0.5, 0.7sec.) 1-4 Operating seismic intensity Target value not to operate at less than 130 gal, and operate within 5 sec. At 200gal. \*: 1 gal (cm/s²): 0.001G. 2.5 degree MIN. from the horizontal 1-5 Returning angle (From operating condition) 50msec. MIN. (cycle: 0.3, 0.5, 0.7 sec./200gal) 1-6 On time ON Output Time **OFF** On time On time 1-7 Return mechanism Self-reset ±0.5 degree MAX. from the horizontal 1-8 Permissible mounting level 1-9 Gradient of sensitivity 20gal MAX. / 1 degree Single pole single throw (NC contacts / slow action) 1-10 Contact form 1 min. MAX.(mounting level ±0.5 degree MAX.) 1-11 Returning time #187 quick connect /solder terminal (thickness=0.5mm) 1-12 Terminal Pitch: 30mm 2 screws(M3) 1-13Mounting Height of the product : 5.3mm (Please refer to drawing in detail.) Soldering iron : temperature  $350\pm10^{\circ}$ C, 3 sec. MAX. 1-14 Soldering

# **OMRON**

## 2. ELECTRICAL CHARACTERISTICS

2-1 Ratings

5VDC, 0.1mA to 30VDC, 100mA (Resistive load)

#### 2-2 Insulation resistance and dielectric strength

	Insulation resistance	Dielectric* strength
Measuring parts	(250 VDC Megger)	(50 to 60 Hz 1 minute)
Between each terminal **		
of the same polarity	100 M Ω MIN.	250 VAC

- \* Leak current is 1mA MAX.
- \*\* To measure off condition

2-3 Contact resistance

100 m Ω MAX. (Initial value)

### 3. MECHANICAL CHARACTERISTICS

3-1 Vibration during transporting

Must be free from any malfunctions both electrically and mechanically

Condition Vibration : 200 gal (1cycle : 0.5 sec.)

Vibration direction : in the three axial directions

Time : Total 50 hours

\* Operating seismic intensity should be 130 to 200gal.

3-2 Shock

Must be free from any malfunctions both electrically and mechanically

Condition

Acceleration

: 980 m/s<sup>2</sup> (100G) 3 times

Shock direction: in the three axial directions

3-3 Shock during transporting

Must be free from any malfunctions both electrically and mechanically

The box which packaged switches are dropped from  $50\pm1\mathrm{cm}$  high toward a composite plate.

(thickness 30mm MIN.)

3-4 Terminal strength

Must be free from any malfunctions both electrically and mechanically (Refer to Note2.)

Apply force to the terminal, 78.4N vertically and 49N horizontally ,1 minute each.

# 4. ENVIRONMENT CHARACTERISTICS

# 4-1 Operating temperature and humidity

Temperature : -25℃ to + 60℃ (No icing and condensation)

Humidity: 45 to 95 %RH

# 4-2 Storage temperature and humidity

Temperature : -25°C to + 60°C (No icing and condensation)

Humidity: 45 to 95 %RH

# 5. ENDURANCE CHARACTERISTICS

#### 5-1 Sait spray

The switch is sprayed with  $5\pm0.5\%$  salt water for 96 hours.

No remarkable corrosion is allowed and must be free from any malfunctions both electrically and mechanically

Contact resistance should be 100  $\Omega$  MAX. (To measure after salt is removed by water and the switch dries well.)

## 5-2 Moisture Endurance

Must be free form any malfunctions both electrically and mechanically after the switch is left in a temperature of  $40\pm2\%$  and humidity of 90 to 98%RH for 240 hours. (To measure after the switch dries well.)

#### 5-3 Oil Endurance

Change of weight must be 20% MAX, after the switch is dipped in Gasoline 1 at  $20\pm5\%$  for 24 hours.

## 5-4 Heat Endurance

Must be free from any malfunctions both electrically and mechanically after the switch is left in a temperature of  $70\pm5\%$  for 96 hours.

## 5-5 Cold Endurance

Must be free from any malfunctions both electrically and mechanically after the switch is left in a temperature of  $-35\pm5\%$  for 96 hours.

# 5-6 High temperature/humidity

Must be free from any malfunctions both electrically and mechanically after the switch is left in a temperature of  $70\pm2\%$  and humidity of 90 to 98%RH for 240 hours.

#### 5-7 Corrosive gas

H<sub>2</sub>S: 3±1ppm, SO<sub>2</sub>: 10±3ppm, 40°C, 75%RH, 96 hours

Must be free from any malfunctions both electrically and mechanically after the switch is left under above condition. Contact resistance should be 100  $\Omega$  MAX.

#### 6. ELECTRICAL SERVICE LIFE

Must be free from any malfunctions both electrically and mechanically after 5,000 operations under the rated resistive load of 30VDC, 100mA at a frequency of 10 to 20 operations per minute.

### 7. OTHERS

#### Note1.

1) If mounting surface is warped, there is a possibility that switch performance might be changed because of switch deformation when it's mounted. (Warp of mounting surface : 0.3mm MAX.)

Use two M3 screws with spring washers to mount the switch.

Tighten the screws to a torque of 0.4N to 0.6N·m (4 to 6kgf·cm).

- 2) Do not set the switch where its mechanically characteristics is affected badly, like door opening, car passage and other vibration and shock.
- 3) Do not put the switch in direct sunshine.
- 4) Mechanical deterioration caused by water cleaning, water covered, leak of oil and other organic solvent.

  Is not guaranteed by us.

#### Note2.

To be evaluated as "free from any malfunctions both electrically and mechanically" the switch must satisfy following requirements.

When installed the sensor at 0.5 degree from the horizontal.

1) Contact resistance

1ΩMAX.

2) Insulation resistance

10M Ω MIN. (250VDC meggar)

3) Operating seismic intensity More than  $\pm 20\%$  of specified range is not acceptable

4) Dielectric strength

250VAC 50/60Hz for 1 minute (Leak current : 1mA MAX.)

## Note3.

This specification is invalid if we receive no approval or no order replacement of yours within a year since this is submitted. In a case of service parts, we will replace with new specifications.

## Note4.

Others not included in this specifications are subjects to change without notice

